

MK - JB

JB-S



JB-T



FEATURE:

- High quality stainless steel material
- Excitate trimming model for easier installation
- Double layer wire line in PCB
- High quality potentiometer for trimming adjusting
- Protected with surge arrestor

Housing Material	Model Name	Line Connection	Types	Trimpod Adjustment Way	Junction Box Outer Size L*w*H(mm)	Install Size with Scale Body (mm)
Stainless Steel	JB-S	JB03-4-S	4 Lines	Signal Adjustment	192x136x45.5	172x36(Φ7)
		JB03-4-J	4 Lines	Excitation Adjustment		
	JB-T	JB05-4-S	4 Lines	Signal Adjustment	318x160x64	280*62(Φ7) (Hole diameter Φ7)
		JB05-6-S	6 Lines	Signal Adjustment		
		JB05-8-S	8 Lines	Signal Adjustment		
		JB05-10-S	10 Lines	Signal Adjustment		
		JB05-4-J	4 Lines	Excitation Adjustment		
		JB05-6-J	6 Lines	Excitation Adjustment		
		JB05-8-J	8 Lines	Excitation Adjustment		
		JB05-10-J	10 Lines	Excitation Adjustment		
	JB-T	JB06-4-S	4 Lines	Signal Adjustment	318x160x49	280*62(Φ7) (Hole diameter Φ7)
		JB06-6-S	6 Lines	Signal Adjustment		
		JB06-4-J	4 Lines	Excitation Adjustment		
		JB06-6-J	6 Lines	Excitation Adjustment		